

KA2-BD

Installation Instructions

This mounting kit is designed specifically to be used to install the Watts Model A2C-M1 IntelliFlow™ automatic washing machine shutoff valve. **Important Cautions!**

1. This kit contains parts to simplify installation of the Watts IntelliFlow Model A2C-M1. If you are not familiar with piping procedures, we recommend you contact a licensed plumbing contractor to install the Watts A2C-M1 Intelliflow.
2. Prior to beginning installation, read all instructions to familiarize yourself with the components of this kit and the assembly procedures.
3. Additional CPVC tubing, elbows, or fittings may be required to complete your particular installation. You can obtain those items at your local hardware store or lumber yard.


Note: The Union tailpieces supplied with the IntelliFlow are not required when the adapters are used.

Installing the A2C-M1 IntelliFlow Automatic Washing Machine Shutoff Valve

1. Plan where you want to locate the IntelliFlow A2C-M1 and how you want to pipe it in prior to starting the actual installation. This will help you avoid problems later in the process. Refer below to Figure A for typical piping arrangements. Caution! In all cases, be sure the IntelliFlow A2C-M1 or piping does not obstruct the washing machine drain tube as shown in Figures B and C.
2. Shut off water supply to the washing machine shutoff valves.
3. Noting their hot and cold water position, disconnect the washing machine hoses from the shutoff valves.

Figure A

This kit can be used for either left or right or center drain installations with straight or angle shut off valves.



Incorrect Installations




Figure B




Figure C

