For Balancing and Flow Measurement Applications

Job Name	Contractor
Job Location	Approval
Engineer	Contractor's P.O. No.
Approval	Representative

Insulation Systems

Sizes: 2¹/₂" – 6" (65 – 150mm)


Watts Insulation Systems are available in sizes $2^{1/2}$ " – 6" (65 – 150mm) to suit series CSM-91 circuit balancing valves and series TDV Triple Duty Combination Valves.

The outside shell is a preformed, removable PVC jacket to meet ASTM D 1784/class 14253-C, MEA #7-87, ASTM-E-84 and ASTM-136 with a flame spread rating of 50 or less. There is provided sufficient mineral fiberglass insulation to meet ASHRAE 90.1-1989 specifications in operating conditions with Maximum Fluid Design Operating Temperature Range of $141^{\circ}\text{F} - 200^{\circ}\text{F}$ ($61^{\circ}\text{C} - 93^{\circ}\text{C}$) and Mean Rating Temperature of 125°F (52°C).

Materials

Outside Shell (2): Zeston 2000 PVC Insulation Batten: Mineral Fiberglass Fastener (4): Stainless steel

Dimensions



Size (DN)		Dimensions				L x W x T	
		A B		}	Insulation Batten Size		
in.	тт	in.	тт	in.	тт	in.	тт
2 ¹ /2	65	20 ¹ / ₂	521	10	254	32 x 15 x 1 ¹ / ₂	813 x 381 x 38
3	80	20	508	11	279	37 x 15 x 1 ¹ / ₂	940 x 381 x 38
4	100	22 ¹ / ₂	572	12 ¹ / ₂	318	40 x 17 x 1 ¹ / ₂	1016 x 432 x 38
5	125	26	660	14	356	48 ¹ /2 x 21 x 1 ¹ /2	1232 x 533 x 38
6	150	30 ¹ / ₂	775	16	406	51 ¹ / ₂ x 22 ¹ / ₂ x 1 ¹ / ₂	1308 x 572 x 38



Installation Instructions





Fig. 3

Fig. 4

- 1. Wrap fiberglass insulation around valve keeping insulation tight around valve neck and body as shown in figs. 2 & 3.
- 2. Cut out insulation around pressure taps so that when diagnostic checks are required, plugs are visible when outside shell is removed as shown in fig. 3.
- 3. Slide 2-Piece outer shell over insulation snugly and then use fastening tacks on top and bottom to secure shell as shown in fig. 4.

USA: 815 Chestnut St., No. Andover, MA 01845-6098; www.wattsreg.com







Watts product specifications in U.S. customary units and metric are approximate and are provided for reference only. For precise measurements, please contact Watts Technical Service. Watts reserves the right to change or modify product design, construction, specifications, or materials without prior notice and without incurring any obligation to make such changes and modifications on Watts products previously or subsequently sold.