## **tekmar**<sup>®</sup> Submittal 24 V (ac) Transformer 013



Job \_\_\_\_\_ Designer \_\_\_\_\_ Contact \_\_\_\_\_

The 24 V (ac) Transformer 013 has a 115 V (ac) primary and a 24 V (ac) secondary with a capacity of 96 VA. A resettable circuit breaker protects the transformer from overloading. A 4" x 4" electrical junction box is included for mounting.



## Specifications

| •  |   |
|--|---|
| 24 V (ac) Transformer 013 96 VA, includes Mounting Box |   |
| Literature   | 013_C, 013_D                                  |
| Packaged weight  | 5.0 lb (2300 g)                               |
| Dimensions   | 4" L x 4" W x 5-7/8" H (102 x 102 x 150 mm)   |
| Approvals  | Transformer UL C US, Electical Box UL and CSA |
| Ambient conditions                                     | Indoor use only, 32 to 122°F (0 to 50°C)      |
| Input power supply                                     | 115 V (ac) ± 10%, 60 Hz                       |
| Output power available                                 | 22 to 30 V (ac), 60 Hz, 96 VA, Class 2        |
| Circuit breaker  | 4 A   |
| Warranty   | Limited 3 Year (See 013_D for full warranty)  |
|  |   |

## **Additional Features**

- 96 VA
- Resettable Circuit Breaker
- NEC/CEC Class 2 Circuits
- Includes 4" x 4" Electrical Box



tekmar Control Systems Ltd., A Watts Water Technologies Company. Head Office: 5100 Silver Star Road, Vernon, B.C. Canada V1B 3K4, 250-545-7749, Fax. 250-545-0650 Web Site: www.tekmarControls.com